

Mean-square exponential stability of exact and numerical solutions for neutral stochastic delay differential equations with Markovian switching

Jina Yang*

Ky Quan Tran[†]

Abstract

This paper investigates the mean-square exponential stability of neutral stochastic differential delay equations (NSDDEs) with Markovian switching. The analysis addresses the complexities arising from the interaction between the neutral term, time-varying delays, and structural changes governed by a continuous-time Markov chain. We establish novel and practical criteria for the mean-square exponential stability of both the underlying system and its numerical approximations via the Euler-Maruyama method. Furthermore, we prove that the numerical scheme can reproduce the exponential decay rate of the true solution with arbitrary accuracy, provided the step size is sufficiently small. The theoretical results are supported by a numerical example that illustrates their effectiveness.

Keywords. neutral stochastic delay differential equations; mean-square exponential stability; time-dependent delay; Markovian switching; Euler-Maruyama approximations

*Department of Biostatistics, Brown University, 121 South Main Street, Providence, Rhode Island, USA 02912, jina_yang@brown.edu

[†]Department of Applied Mathematics and Statistics, State University of New York - Korea, Yeonsu-Gu, Incheon, Korea 21985, ky.tran@stonybrook.edu

1 Introduction

This work aims to investigating the mean-square exponential stability of a class of neutral stochastic delay differential equations (NSDDEs) with Markovian switching. Our motivation stems from the need to model complex real-world systems where the current state depends on past events. Such stochastic processes, which incorporate a neutral term, a time-varying delay, and white noise, are widely applicable in many disciplines; see [7, 23] and the references therein.

It has been recognized that stochastic processes incorporating time-dependent delays are increasingly vital in fields ranging from biology to engineering [2, 16]. Unlike constant delays, time-dependent delays capture the dynamic nature of these systems. Furthermore, as presented in [6] and [23], the inclusion of Markovian switching is essential to describe random environmental influences. What happens if the environment changes randomly? The asymptotic behavior becomes significantly more complex than in a fixed environment. In particular, there are examples (see [25]) where a system that is stable in some fixed environments and unstable in others can be stabilized or destabilized purely by choosing suitable switching rates.

The literature on the exponential stability of NSDDEs is rich. By and large, intensive studies of NSDDEs without switching can be found in [7, Chapter 6]. There have also been efforts to find criteria for the mean-square exponential stability of NSDDEs with Markovian switching. However, existing works such as [3, 18, 21, 28] focus primarily on cases where the delay is either constant or differentiable. Meanwhile, [5] treats a class of NSDDEs with non-differentiable time delays. To the best of our knowledge, there are no explicit criteria for the mean-square exponential stability of NSDDEs with Markovian switching subject to arbitrary time-dependent delays. Thus, a natural question arises: Can we develop an explicit criterion for the mean-square exponential stability of NSDDEs with arbitrary time-dependent delays?

To answer this question, we seek a criterion given in terms of the system coefficients and the generator of the Markovian switching, without posing specific technical conditions on the time-dependent delay functions. This objective motivates the first part of our current paper.

Because of the stochasticity, nonlinearity, and hybrid switching behavior, closed-form solutions for these systems are virtually impossible to obtain. Hence, numerical methods are often the only viable alternative. A wide range of numerical methods have been developed to solve NSDDEs, with considerable attention given to preserving their exponential stability [17, 22, 26, 29]. For instance, the exponential stability of the Euler–Maruyama (EM) method has been studied in [8, 14, 27, 29]. The backward Euler–Maruyama and theta Euler–Maruyama

approximations have also been investigated in [3, 9, 10, 11, 12, 14, 26], along with studies examining highly nonlinear NSDDEs under specific scenarios [8, 17, 24].

Focusing on the long-time behavior of the numerical solutions, a question naturally arises: Given a stable equation, can the numerical solutions reproduce the stability? This question motivates the second part of our paper. It should be noted that a key limitation in [3, 18, 28] is that the time-dependent delay $\delta(t)$ is assumed to be either a constant function or differentiable with $\sup_{t \geq 0} \delta'(t) < 1$. This assumption is also prevalent in other existing work [3, 4, 10, 11, 12, 26].

In this paper, our effort is placed on overcoming these limitations on the time-dependent delay $\delta(t)$ by using a novel comparison approach via contradiction. While our approach is motivated by developments in [14, 15], the stability analysis herein is considerably more challenging due to the need to treat Markovian switching.

The rest of the paper is arranged as follows. Section 2 begins with the problem formulation. Section 3 presents a new criterion for the mean-square exponential stability of the exact solutions. Section 4 focuses on the stability of the EM numerical solutions for NSDDEs. Moreover, an example is presented for illustrative purposes. Finally, Section 5 concludes the paper with a few more remarks.

Notation. Let \mathbb{R}_+ be the set of nonnegative real numbers, \mathbb{N} be the set of positive integers, and $\mathbb{N}_0 = \mathbb{N} \cup \{0\}$. For two real numbers c_1 and c_2 , $c_1 \vee c_2$ denotes $\max\{c_1, c_2\}$. For a real number u , $\lfloor u \rfloor$ is the integer part (or the floor) of u . For a matrix $A \in \mathbb{R}^{d_1 \times d_2}$, A^\top denotes its transpose and $|A| = \sqrt{\text{trace}(A^\top A)}$ is its trace norm. For $x = (x_1, \dots, x_d)^\top \in \mathbb{R}^d$, its Euclidean norm is denoted by $|x| = (\sum_{i=1}^d x_i^2)^{1/2}$. For a set M , the indicator function of M is denoted by $\mathbf{1}_M$. For a constant $r > 0$, let $C([-r, 0], \mathbb{R}^d)$ be the Banach space of all continuous functions on $[-r, 0]$, endowed with the norm $\|\phi\| = \max_{s \in [-r, 0]} |\phi(s)|$ for $\phi \in C([-r, 0], \mathbb{R}^d)$. For a σ -algebra \mathcal{F}_0 , let $C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d)$ be the family of \mathcal{F}_0 -measurable bounded $C([-r, 0], \mathbb{R}^d)$ -valued random variables.

2 Formulation

We begin by specifying the probabilistic framework. To facilitate the analysis, we work with a complete probability space $(\Omega, \mathcal{F}, \mathbb{P}, \{\mathcal{F}_t\})$, where the filtration $\{\mathcal{F}_t\}$ satisfies the usual conditions (i.e., it is right-continuous and \mathcal{F}_0 contains all \mathbb{P} -null sets). Let $w(t)$ be an m -dimensional standard Brownian motion. To model the regime switching, we introduce a continuous-time Markov chain $\alpha(t)$ taking values in a finite state space $\mathcal{M} = \{1, 2, \dots, m_0\}$ (where $m_0 \in \mathbb{N}$) with generator $Q = (q_{ij}) \in \mathbb{R}^{m_0 \times m_0}$. We assume that $w(t)$ and $\alpha(t)$ are

independent and adapted to $\{\mathcal{F}_t\}$.

The evolution of the switching process $\alpha(t)$ is governed by the transition probability specification:

$$\mathbb{P}(\alpha(t + \Delta t) = j | \alpha(t) = i) = \begin{cases} q_{ij}\Delta t + o(\Delta t) & \text{if } i \neq j, \\ 1 + q_{ii}\Delta t + o(\Delta t) & \text{if } i = j, \end{cases} \quad (2.1)$$

where $q_{ij} \geq 0$ for $i \neq j$ and the row sums satisfy $\sum_{j \in \mathcal{M}} q_{ij} = 0$ for any $i \in \mathcal{M}$.

Our main interest lies in the dynamics of a NSDDE. Let $r > 0$ be the delay bound. We consider Borel measurable functions $f : \mathbb{R}^d \times \mathbb{R}^d \times \mathcal{M} \rightarrow \mathbb{R}^d$, $g : \mathbb{R}^d \times \mathbb{R}^d \times \mathcal{M} \rightarrow \mathbb{R}^{d \times m}$, $G : \mathbb{R}^d \times \mathcal{M} \rightarrow \mathbb{R}^d$, and a time-dependent delay function $\delta : \mathbb{R}_+ \rightarrow [0, r]$. The state trajectory $X(t)$ is determined by the following system:

$$\begin{aligned} d(X(t) - G(X(t - \delta(t)), \alpha(t))) &= f(X(t), X(t - \delta(t)), \alpha(t)) dt \\ &+ g(X(t), X(t - \delta(t)), \alpha(t)) dw(t) \quad \text{for } t \geq 0. \end{aligned} \quad (2.2)$$

To ensure the system is well-defined, we impose the initial condition $(\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M}$, such that

$$X(s) = \xi(s) \quad \text{for any } s \in [-r, 0], \quad \alpha(0) = i_0. \quad (2.3)$$

To proceed with the analysis, we require standard regularity conditions on the coefficients. Throughout the paper, we assume that the functions $f(x, y, i)$ and $g(x, y, i)$ satisfy a local Lipschitz condition. That is, for each $n \in \mathbb{N}$, there exists a constant $\tilde{K}_n > 0$ such that

$$|f(x, y, i) - f(\bar{x}, \bar{y}, i)| + |g(x, y, i) - g(\bar{x}, \bar{y}, i)| \leq \tilde{K}_n(|x - \bar{x}| + |y - \bar{y}|)$$

whenever $|x| \vee |y| \leq n$, $|\bar{x}| \vee |\bar{y}| \leq n$, and $i \in \mathcal{M}$. Furthermore, we assume $f(0, 0, i) = 0 \in \mathbb{R}^d$ and $g(0, 0, i) = 0 \in \mathbb{R}^{d \times m}$ for any $i \in \mathcal{M}$. Regarding the neutral term, we assume $G(0, i) = 0 \in \mathbb{R}^d$ and that there exists a contraction constant $\kappa \in (0, 1)$ satisfying

$$|G(x, i) - G(y, i)| \leq \kappa|x - y| \quad \text{for } x, y \in \mathbb{R}^d, \quad i \in \mathcal{M}.$$

As a standing assumption, we posit that for each initial condition $(\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M}$, Eq. (2.2) admits a unique global solution $X^{\xi, i_0}(\cdot)$ satisfying (2.3). It has been recognized that if $f(\cdot)$ and $g(\cdot)$ satisfy the linear growth condition; that is, there exists $\tilde{K}_0 > 0$ such that

$$|f(x, y, i)| + |g(x, y, i)| \leq \tilde{K}_0(1 + |x| + |y|) \quad \text{for } x, y \in \mathbb{R}^d, \quad i \in \mathcal{M},$$

then the existence and uniqueness of the global solution are guaranteed; see [7, Theorem 2.2, p. 204].

Our ultimate goal is to analyze the stability of these solutions. We adopt the following definition of mean-square exponential stability.

Definition 2.1. Eq. (2.2) is said to be mean-square exponentially stable if there exist constants $K > 0$ and $\lambda > 0$ such that

$$\mathbb{E}|X^{\xi, i_0}(t)|^2 \leq K e^{-\lambda t} \mathbb{E}\|\xi\|^2 \quad \text{for any } (\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M} \text{ and } t \geq 0.$$

3 Stability of the exact solutions

To proceed with the stability analysis, we require the following assumption.

(H) There are positive constants $\{p_i\}_{i \in \mathcal{M}}$ and nonnegative constants c_0 , c_1 , and c_2 such that

$$\begin{aligned} 2(x - G(y, i))^{\top} f(x, y, i) + |g(x, y, i)|^2 + \sum_{j \in \mathcal{M}} q_{ij} \frac{p_j}{p_i} |x - G(y, i)|^2 \\ \leq -c_0 |x - G(y, i)|^2 + c_1 |x|^2 + c_2 |y|^2 \end{aligned} \quad (3.1)$$

for any $(x, y, i) \in \mathbb{R}^d \times \mathbb{R}^d \times \mathcal{M}$.

For the sake of notational simplicity, we define

$$p_{\max} = \max\{p_i : i \in \mathcal{M}\}, \quad p_{\min} = \min\{p_i : i \in \mathcal{M}\}, \quad r_p = \frac{p_{\max}}{p_{\min}},$$

and

$$Z(t) = X(t) - G(X(t - \delta(t)), \alpha(t)) \quad \text{for } t \geq 0.$$

To highlight the dependence on the initial condition (2.3), the process $Z(t)$ is denoted by $Z^{\xi, i_0}(t)$.

Lemma 3.1. Assume that there exist constants $T > 0$, $K > 0$, and $\lambda > 0$ such that

$$\mathbb{E}[p_{\alpha(t)} |Z^{\xi, i_0}(t)|^2] \leq K e^{-\lambda t} \mathbb{E}\|\xi\|^2 \quad \text{for any } (\xi, i_0, t) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M} \times [0, T].$$

Then

$$\mathbb{E}[p_{\alpha(t)} |X^{\xi, i_0}(t)|^2] \leq \frac{r_p}{(1 - \kappa e^{\lambda r/2})^2} K e^{-\lambda t} \mathbb{E}\|\xi\|^2$$

and

$$\mathbb{E}[p_{\alpha(t)} |X^{\xi, i_0}(t - \delta(t))|^2] \leq \frac{r_p}{(1 - \kappa e^{\lambda r/2})^2} K e^{-\lambda(t - \delta(t))} \mathbb{E}\|\xi\|^2$$

for any $(\xi, i_0, t) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M} \times [0, T]$.

Proof. To proceed, we recall the Hölder inequality. For any $\varepsilon > 0$,

$$|x + y|^2 \leq (1 + \varepsilon) \left(|x|^2 + \frac{|y|^2}{\varepsilon} \right) \quad \text{for } x, y \in \mathbb{R}^d;$$

see [7, Lemma 4.1, p. 211]. By setting $v \in (0, 1)$ and $\varepsilon = \frac{v}{1-v}$, we obtain

$$|x + y|^2 \leq \frac{1}{1-v}|x|^2 + \frac{1}{v}|y|^2 \quad \text{for } x, y \in \mathbb{R}^d. \quad (3.2)$$

For the sake of notational simplicity, we write $X(t) = X^{\xi, i_0}(t)$ and $Z(t) = X(t) - G(X(t - \delta(t)), \alpha(t))$. Let $K_1 = K\mathbb{E}\|\xi\|^2$. In view of (3.2), for any $t \in [0, T]$, it follows that

$$|Z(t) + G(X(t - \delta(t)), \alpha(t))|^2 \leq \frac{1}{1-v}|Z(t)|^2 + \frac{1}{v}|G(X(t - \delta(t)), \alpha(t))|^2.$$

It follows that

$$|X(t)|^2 \leq \frac{1}{1-v}|Z(t)|^2 + \frac{\kappa^2}{v}|X(t - \delta(t))|^2.$$

Multiplying by $e^{\lambda t}$ and taking expectations, we arrive at

$$\begin{aligned} e^{\lambda t}\mathbb{E}|X(t)|^2 &\leq \frac{1}{1-v}e^{\lambda t}\mathbb{E}|Z(t)|^2 + \frac{\kappa^2}{v}e^{\lambda t}\mathbb{E}|X(t - \delta(t))|^2 \\ &\leq \frac{1}{1-v}e^{\lambda t}\mathbb{E}|Z(t)|^2 + \frac{\kappa^2}{v}e^{-\lambda(t-\delta(t))+\lambda t}e^{\lambda(t-\delta(t))}\mathbb{E}|X(t - \delta(t))|^2 \\ &\leq \frac{1}{1-v}e^{\lambda t}\mathbb{E}|Z(t)|^2 + \frac{\kappa^2}{v}e^{\lambda\delta(t)}\left(\sup_{s \in [0, T)} e^{\lambda s}\mathbb{E}|X(s)|^2\right) \\ &\leq \frac{1}{1-v}e^{\lambda t}\mathbb{E}|Z(t)|^2 + \frac{\kappa^2}{v}e^{\lambda r}\left(\sup_{s \in [0, T)} e^{\lambda s}\mathbb{E}|X(s)|^2\right); \end{aligned}$$

which leads to

$$e^{\lambda t}\mathbb{E}|X(t)|^2 \leq \frac{1}{1-v}e^{\lambda t}\mathbb{E}|Z(t)|^2 + \frac{\kappa^2}{v}e^{\lambda r}\left(\sup_{s \in [0, T)} e^{\lambda s}\mathbb{E}|X(s)|^2\right).$$

Setting $v = \kappa e^{\lambda r/2}$ and noting that

$$e^{\lambda t}\mathbb{E}|Z(t)|^2 \leq \frac{1}{p_{\min}}e^{\lambda t}\mathbb{E}[p_{\alpha(t)}|Z(t)|^2] \leq \frac{1}{p_{\min}}K_1$$

yields

$$e^{\lambda t}\mathbb{E}|X(t)|^2 \leq \frac{K_1}{(1 - \kappa e^{\lambda r/2})p_{\min}} + \kappa e^{\lambda r/2}\left(\sup_{s \in [0, T)} e^{\lambda s}\mathbb{E}|X(s)|^2\right) \quad \text{for } t \in [0, T]. \quad (3.3)$$

Taking the supremum over $t \in [0, T]$ in (3.3) yields

$$\sup_{t \in [0, T)} e^{\lambda t}\mathbb{E}|X(t)|^2 \leq \frac{K_1}{(1 - \kappa e^{\lambda r/2})^2 p_{\min}}.$$

This implies

$$\mathbb{E}|X(t)|^2 \leq \frac{K_1}{(1 - \kappa e^{\lambda r/2})^2 p_{\min}}e^{-\lambda t} \quad \text{for } t \in [0, T]. \quad (3.4)$$

Consequently,

$$\mathbb{E}[p_{\alpha(t)}|X(t)|^2] \leq p_{\max}\mathbb{E}|X(t)|^2 \leq \frac{K_1 p_{\max}}{(1 - \kappa e^{\lambda r/2})^2 p_{\min}} e^{-\lambda t} \quad \text{for } t \in [0, T];$$

that is,

$$\mathbb{E}[p_{\alpha(t)}|X(t)|^2] \leq \frac{r_p K_1}{(1 - \kappa e^{\lambda r/2})^2} e^{-\lambda t} \quad \text{for } t \in [0, T],$$

where $r_p = \frac{p_{\max}}{p_{\min}}$.

For $t \in [0, T)$ with $t - \delta(t) \geq 0$, in view of (3.4), we have

$$\begin{aligned} \mathbb{E}[p_{\alpha(t)}|X(t - \delta(t))|^2] &\leq p_{\max}\mathbb{E}|X(t - \delta(t))|^2 \\ &\leq \frac{r_p K_1}{(1 - \kappa e^{-\lambda r/2})^2} e^{-\lambda(t - \delta(t))}. \end{aligned}$$

Note that the inequality remains valid if $t - \delta(t) < 0$. Consequently,

$$\mathbb{E}[p_{\alpha(t)}|X(t - \delta(t))|^2] \leq \frac{r_p K_1}{(1 - \kappa e^{-\lambda r/2})^2} e^{-\lambda(t - \delta(t))} \quad \text{for } t \in [0, T].$$

The conclusion follows. \square

We are now in a position to present a criterion for the mean-square exponential stability of Eq. (2.2).

Theorem 3.2. *Suppose that assumption (H) is satisfied. In addition, assume that*

$$-c_0 + \frac{r_p}{(1 - \kappa)^2}(c_1 + c_2) < 0. \quad (3.5)$$

Then Eq. (2.2) is mean-square exponentially stable. Specifically, for any $(\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M}$, $\mathbb{E}|X^{\xi, i_0}(t)|^2$ exponentially decays with a rate no less than λ_0 , which is the unique positive root in $(0, -\frac{2}{r} \ln \kappa)$ of

$$-c_0 + \frac{r_p}{(1 - \kappa e^{\lambda_0 r/2})^2}(c_1 + c_2 e^{\lambda_0 r}) + \lambda_0 = 0.$$

Proof. Let $(\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M}$. Without loss of generality, we assume $\mathbb{E}\|\xi\|^2 > 0$. For the sake of notational simplicity, we write $X(t) = X^{\xi, i_0}(t)$ and $Z(t) = X(t) - G(X(t - \delta(t)), \alpha(t))$ for any $t \geq 0$.

Define

$$H(\rho) = -c_0 + \frac{r_p}{(1 - \kappa e^{\rho r/2})^2}(c_1 + c_2 e^{\rho r}) + \rho \quad \text{for } \rho \in (0, -\frac{2}{r} \ln \kappa).$$

Observe that the function $H(\cdot)$ is continuous and strictly increasing on $(0, -\frac{2}{r} \ln \kappa)$. In view of (3.5), $\lim_{\rho \rightarrow 0} H(\rho) < 0$. Moreover, it is evident that $\lim_{\rho \rightarrow -\frac{2}{r} \ln \kappa} H(\rho) = \infty$. Then on the interval $(0, -\frac{2}{r} \ln \kappa)$, the equation $H(\rho) = 0$ has a unique solution $\rho = \lambda_0$. Let $\lambda \in (0, \lambda_0]$ and $\beta = (1 - \kappa e^{\lambda r/2})^{-2}$. Since $H(\cdot)$ is strictly increasing on $(0, -\frac{2}{r} \ln \kappa)$, we have $H(\lambda) \leq H(\lambda_0) = 0$. Consequently,

$$-c_0 + r_p \beta (c_1 + c_2 e^{\lambda r}) \leq -\lambda. \quad (3.6)$$

Let $K = 2(1 + \kappa^2) \sum_{i \in \mathcal{M}} p_i$ and $K_1 = K \mathbb{E} \|\xi\|^2$. Then

$$\mathbb{E}[p_{\alpha(t)} |Z(t)|^2] < K_1 e^{-\lambda t} \quad \text{when } t = 0. \quad (3.7)$$

We aim to show that

$$\mathbb{E}[p_{\alpha(t)} |Z(t)|^2] < K_1 e^{-\lambda t} \quad \text{for any } t \geq 0. \quad (3.8)$$

Let us consider the real-valued functions $\Phi(t)$ and $\Psi(t)$ defined by

$$\Phi(t) = \mathbb{E}[p_{\alpha(t)} |Z(t)|^2], \quad \Psi(t) = K_1 e^{-\lambda t} \quad \text{for } t \geq 0.$$

Noting that the trajectories of $Z(t)$ are continuous, while the trajectories of $p_{\alpha(t)}$ are right-continuous, we see that $\Phi(t)$ is right-continuous on the interval $[0, \infty)$. Furthermore, it is clear that $\Psi(t)$ is continuous on $[0, \infty)$. Were the statement (3.8) false, by the right-continuity of $\Phi(t)$ and the continuity of $\Psi(t)$, there would exist $t_* > 0$ such that

$$\Phi(t) < \Psi(t) \quad \text{for } t \in [0, t_*), \quad \Phi(t_*) \geq \Psi(t_*). \quad (3.9)$$

Fix a constant $c > c_0$. Applying the Itô formula to the process $Z(t)$ given by Eq. (2.2) and taking expectation of both sides of the resulting equation, we derive

$$e^{ct_*} \mathbb{E}[p_{\alpha(t_*)} |Z(t_*)|^2] = \mathbb{E}[p_{i_0} |Z(0)|^2] + \int_0^{t_*} e^{cs} \mathbb{E}[\mathcal{H}(s)] ds, \quad (3.10)$$

where

$$\begin{aligned} \mathcal{H}(s) = & c p_{\alpha(s)} |Z(s)|^2 + \sum_{j \in \mathcal{M}} q_{\alpha(s)j} p_j (X(s) - G(X(s - \delta(s)), \alpha(s))) \\ & + 2 p_{\alpha(s)} (Z(s))^\top f(X(s), X(s - \delta(s)), \alpha(s)) \\ & + p_{\alpha(s)} |g(X(s), X(s - \delta(s)), \alpha(s))|^2 \quad \text{for } s \in [0, t_*). \end{aligned}$$

In view of (3.1), for any $s \in [0, t_*]$,

$$\mathcal{H}(s) \leq (c - c_0) p_{\alpha(s)} |Z(s)|^2 + c_1 p_{\alpha(s)} |X(s)|^2 + c_2 p_{\alpha(s)} |X(s - \delta(s))|^2.$$

Hence,

$$\begin{aligned}\mathbb{E}[\mathcal{H}(s)] &\leq (c - c_0)\mathbb{E}[p_{\alpha(s)}|Z(s)|^2] \\ &\quad + c_1\mathbb{E}[p_{\alpha(s)}|X(s)|^2] + c_2\mathbb{E}[p_{\alpha(s)}|X(s - \delta(s))|^2] \quad \text{for } s \in [0, t_*].\end{aligned}$$

By virtue of Lemma 3.1, for any $s \in [0, t_*]$,

$$\mathbb{E}[p_{\alpha(s)}|X(s)|^2] \leq r_p\beta K_1 e^{-\lambda s}, \quad \mathbb{E}[p_{\alpha(s)}|X(s - \delta(s))|^2] \leq r_p\beta K_1 e^{-\lambda(s - \delta(s))}.$$

Hence,

$$\mathbb{E}[\mathcal{H}(s)] \leq (c - c_0)K_1 e^{-\lambda s} + c_1 r_p \beta K_1 e^{-\lambda s} + c_2 r_p \beta K_1 e^{-\lambda s} \quad \text{for } s \in [0, t_*].$$

Combining this with the property of λ in (3.6) yields

$$\begin{aligned}\int_0^{t_*} e^{cs} \mathbb{E}[\mathcal{H}(s)] ds &\leq K_1 \int_0^{t_*} e^{(c-\lambda)s} [c - c_0 + c_1 r_p \beta + c_2 r_p \beta e^{\lambda r}] ds \\ &\leq K_1 \int_0^{t_*} e^{(c-\lambda)s} (c - \lambda) ds \\ &= K_1 (e^{(c-\lambda)t_*} - 1).\end{aligned}\tag{3.11}$$

It follows from (3.10) and (3.11) that

$$\begin{aligned}e^{ct_*} \mathbb{E}[p_{\alpha(t_*)}|Z(t_*)|^2] &\leq \mathbb{E}[p_{i_0}|Z(0)|^2] + K_1 (e^{(c-\lambda)t_*} - 1) \\ &< K_1 e^{(c-\lambda)t_*},\end{aligned}$$

where we have used that $\Phi(0) = \mathbb{E}[p_{i_0}|Z(0)|^2] < K_1$; see (3.7). Consequently,

$$\Phi(t_*) = \mathbb{E}[p_{\alpha(t_*)}|Z(t_*)|^2] < K_1 e^{-\lambda t_*} = \Psi(t_*).$$

This contradicts the second statement in (3.9). Consequently, (3.8) is verified. By Lemma 3.1, Eq. (2.2) is mean-square exponentially stable and the conclusion follows. \square

4 Stability of EM approximations

We proceed to construct the EM numerical solutions for Eq. (2.2) subject to the initial condition (2.3). Let the step size ε be a fraction of r ; specifically, we set $\varepsilon = r/N$ for some positive integer $N > r$. To approximate the switching component, let $\{\alpha_n\}_{n \geq 0}$ denote the discrete-time Markov chain characterized by the one-step transition probability matrix $e^{\varepsilon Q}$ with $\alpha_0 = i_0$. For the detailed method of simulating the chain $\{\alpha_n\}$, we refer the reader to [6, p. 112].

The application of the EM approximation method to Eq. (2.2) yields an approximation sequence $\{Y_n\}_{n \geq -N}$. To ensure that the EM approximation sequence is well-defined, we impose the following:

$$Y_{-(N+1)} = \xi(-N\varepsilon), \quad \delta(-\varepsilon) = \delta(0), \quad \alpha_{-1} = \alpha_0.$$

Then

$$\begin{aligned} Y_n &= \xi(n\varepsilon), \quad -N \leq n \leq 0, \\ Y_{n+1} &= Y_n + G(Y_{n-R_n}, \alpha_n) - G(Y_{n-1-R_{n-1}}, \alpha_{n-1}) + f(Y_n, Y_{n-R_n}, \alpha_n)\varepsilon \\ &\quad + g(Y_n, Y_{n-R_n}, \alpha_n)\Delta w_n \quad \text{for } n \in \mathbb{N}_0, \end{aligned} \quad (4.1)$$

where

$$\Delta w_n = w((n+1)\varepsilon) - w(n\varepsilon), \quad R_n = \lfloor \delta(n\varepsilon)/\varepsilon \rfloor.$$

We recall that $\lfloor \delta(n\varepsilon)/\varepsilon \rfloor$ denotes the integer part of $\delta(n\varepsilon)/\varepsilon$. To explicitly indicate the dependence on the initial conditions $Y_n = \xi(n\varepsilon)$ for $-N \leq n \leq 0$ and $\alpha_0 = i_0$, we denote the sequence $\{Y_n\}$ generated by (4.1) as $\{Y_n^{\xi, i_0}\}$.

To facilitate the stability analysis of the numerical scheme, we first establish the following auxiliary results.

Lemma 4.1. *Let $\lambda \in (0, -\frac{2}{r} \ln \kappa)$ and $\varepsilon \in (0, 1)$ be chosen such that $\lambda < -\frac{2 \ln \kappa}{r+\varepsilon}$. Define*

$$\beta(\varepsilon) = \frac{1}{(1 - \kappa e^{\lambda(r+\varepsilon)/2})^2}.$$

Let $\{Y_n\}$ denote the EM approximation sequence, and let $Z_n = Y_n - G(Y_{n-1-R_{n-1}}, \alpha_{n-1})$ and $\bar{p}_n = p_{\alpha_n}$ for $n \in \mathbb{N}_0$. Suppose further that there exist constants $k \in \mathbb{N}$ and $K > 1$ such that

$$\mathbb{E}[\bar{p}_n |Z_n|^2] \leq K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2 \quad \text{for } n = 0, 1, \dots, k. \quad (4.2)$$

Then the following assertions hold:

(a) *For any $n = 0, 1, \dots, k$,*

$$\mathbb{E}|Z_n|^2 \leq \frac{1}{p_{\min}} K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2. \quad (4.3)$$

(b) *For any $n = -N, \dots, 0, 1, \dots, k$,*

$$\mathbb{E}|Y_n|^2 \leq \frac{1}{p_{\min}} \beta(\varepsilon) K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2. \quad (4.4)$$

(c) *For any $n = 0, 1, \dots, k$,*

$$\mathbb{E}[\bar{p}_n |Y_n|^2] \leq r_p \beta(\varepsilon) K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2 \quad (4.5)$$

and

$$\mathbb{E}[\bar{p}_n |Y_{n-1-R_{n-1}}|^2] \leq r_p e^{\lambda(r+\varepsilon)} \beta(\varepsilon) K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2. \quad (4.6)$$

Proof. (a) The inequality (4.3) follows directly from the assumption (4.2) and the definition of p_{\min} .

(b) Regarding (b), subject to the validity of (4.3), the detailed proof of (4.4) is provided in [14, Lemma 3.1].

(c) We proceed to prove (c). By virtue of (4.4), for any $n = 0, 1, \dots, k$, we have

$$\begin{aligned}\mathbb{E}[\bar{p}_n | Y_n|^2] &\leq p_{\max} \mathbb{E}|Y_n|^2 \\ &\leq \frac{p_{\max}}{p_{\min}} \beta(\varepsilon) K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2;\end{aligned}$$

consequently, (4.5) is verified.

(d) Finally, for assertion (d), in view of (4.4), it follows that

$$\begin{aligned}\mathbb{E}[\bar{p}_n | Y_{n-1-R_{n-1}}|^2] &\leq p_{\max} \mathbb{E}|Y_{n-1-R_{n-1}}|^2 \\ &\leq \frac{p_{\max}}{p_{\min}} \beta(\varepsilon) K e^{-\lambda(n-1-R_{n-1})\varepsilon} \mathbb{E}\|\xi\|^2 \\ &\leq r_p e^{\lambda(r+\varepsilon)} \beta(\varepsilon) K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2.\end{aligned}$$

This yields the desired inequality (4.6). Note that in the last step, we have utilized the fact that $R_{n-1}\varepsilon \leq r$. The proof is thus complete. \square

Remark 4.2. For any $i, j \in \mathcal{M}$ and $\varepsilon \in (0, 1)$, let $p_{ij}(\varepsilon)$ be the (i, j) entry in the matrix $\exp(\varepsilon Q)$. Define

$$\|Q\|_{\infty} = \max\{|q_{ij}| : i, j = 1, 2, \dots, m_0\}.$$

Note that

$$\exp(\varepsilon Q) = \mathbf{I} + \varepsilon Q + \varepsilon^2 \sum_{k=2}^{\infty} \frac{\varepsilon^{k-2} Q^k}{k!},$$

where \mathbf{I} is the $m_0 \times m_0$ identity matrix. Let $\tau_{ij}(\varepsilon)$ be the (i, j) entry in $\sum_{k=2}^{\infty} \frac{\varepsilon^{k-2} Q^k}{k!}$. It has been proved in [20, Lemma 3.2] that

$$|\tau_{ij}(\varepsilon)| \leq \exp(m_0 \|Q\|_{\infty}) - 1 - m_0 \|Q\|_{\infty} \quad \text{for any } i, j \in \mathcal{M}, \quad \varepsilon \in (0, 1). \quad (4.7)$$

We turn our attention to the mean-square exponential stability of the EM approximations. The following theorem demonstrates that, provided the step size ε is sufficiently small, the EM approximations faithfully reproduce the mean-square exponential stability of the exact solution. Furthermore, it reveals that the numerical scheme is capable of reproducing the exponential decay rate λ_0 with arbitrary accuracy.

Theorem 4.3. Suppose that the assumptions of Theorem 3.2 are satisfied. In addition, assume that there exists a constant $C_0 > 0$ such that

$$|f(x, y, i)|^2 \leq C_0(|x|^2 + |y|^2) \quad \text{for any } x, y \in \mathbb{R}^d, \quad i \in \mathcal{M}. \quad (4.8)$$

Let $\lambda \in (0, \lambda_0)$ and define $\beta = (1 - \kappa e^{\lambda r/2})^{-2}$. Then there exists a constant $\varepsilon_0 > 0$ such that for any step size $\varepsilon \in (0, \varepsilon_0]$, the EM approximation sequence $\{Y_n\}$ is mean-square exponentially stable. Moreover, we have

$$\limsup_{n \rightarrow \infty} \frac{1}{n\varepsilon} \ln (\mathbb{E}|Y_n^{\xi, i_0}|^2) \leq -\lambda \quad \text{for } (\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M}. \quad (4.9)$$

Proof. The proof is divided into four steps.

Step 1. By virtue of (3.5), we can select a positive constant $\varepsilon_0 < (1/\lambda_0) \vee (-\frac{2}{\lambda} \ln \kappa - r)$ such that

$$-c_0 + c_1 r_p \beta(\varepsilon_0) + c_2 r_p e^{\lambda(r+\varepsilon_0)} + \varepsilon_0 C_1(\varepsilon_0) < -\lambda, \quad (4.10)$$

where

$$\beta(\varepsilon) = \frac{1}{(1 - \kappa e^{\alpha(r+\varepsilon)/2})^2}$$

and

$$C_1(\varepsilon) = \varepsilon r_0 \beta(\varepsilon) p_{\min}^{-1} \left((2\|Q\|_\infty + c_1 + C_0) + C_0 e^{\lambda r} + (2\|Q\|_\infty + c_2) e^{\lambda(1+r)\varepsilon} \right), \quad \varepsilon > 0.$$

Consequently, it follows that

$$-c_0 + c_1 r_p \beta(\varepsilon) + c_2 r_p e^{\lambda(r+\varepsilon)} + \varepsilon C_1(\varepsilon) < -\lambda \quad \text{for } \varepsilon \in (0, \varepsilon_0]. \quad (4.11)$$

For the remainder of the proof, we fix $\varepsilon \in (0, \varepsilon_0]$. Let $(\xi, i_0) \in C_{\mathcal{F}_0}^b([-r, 0], \mathbb{R}^d) \times \mathcal{M}$. For the sake of notational simplicity, let $\{Y_n\} = \{Y_n^{\xi, i_0}\}$ be the approximation sequence given by (4.1), and $Z_n = Y_n - G(Y_{n-1-R_{n-1}}, \alpha_{n-1})$ for $n \in \mathbb{N}_0$. Without loss of generality, assume $\mathbb{E}\|\xi\|^2 > 0$.

Step 2: Let us consider the real-valued sequences $\{\Phi_n\}_{n \geq 0}$ and $\{\Psi_n\}_{n \geq 0}$ defined by

$$\Phi_n := \mathbb{E}[\bar{p}_n |Z_n|^2], \quad \Psi_n := K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2 \quad \text{for } n \in \mathbb{N}_0,$$

where $K_1 = K \mathbb{E}\|\xi\|^2$ and $K = 2(1 + \kappa^2) \sum_{i \in \mathcal{M}} p_i$. Then $\Phi_0 \leq \Psi_0$. We aim to show that

$$\Phi_n = \mathbb{E}[\bar{p}_n |Z_n|^2] \leq K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2 = \Psi_n \quad \text{for } n \in \mathbb{N}_0. \quad (4.12)$$

Were this statement false, there would exist $k \in \mathbb{N}_0$ such that

$$\Phi_n \leq \Psi_n \quad \text{for } 0 \leq n \leq k, \quad \Phi_{k+1} > \Psi_{k+1}. \quad (4.13)$$

Recalling (4.1), we have

$$Z_{k+1} = Z_k + f(Y_k, Y_{k-R_k}, \alpha_k)\varepsilon + g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k.$$

Taking the squared norm on both sides and multiplying by \bar{p}_{k+1} , we obtain

$$\begin{aligned} \bar{p}_{k+1}|Z_{k+1}|^2 &= \bar{p}_{k+1}|Z_k|^2 + \bar{p}_{k+1}|f(Y_k, Y_{k-R_k}, \alpha_k)\varepsilon|^2 + \bar{p}_{k+1}|g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k|^2 \\ &\quad + 2\bar{p}_{k+1}Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k)\varepsilon + 2\bar{p}_{k+1}Z_k^\top g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k \\ &\quad + 2\bar{p}_{k+1}\left(f(Y_k, Y_{k-R_k}, \alpha_k)\varepsilon\right)^\top g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k. \end{aligned} \quad (4.14)$$

It is readily verified that

$$\begin{aligned} \mathbb{E}\left[\bar{p}_{k+1}|g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k|^2\right] &= \varepsilon\mathbb{E}\left[p_{k+1}|g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right], \\ \mathbb{E}\left[2\bar{p}_{k+1}Z_k^\top g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k\right] &= 0, \\ \mathbb{E}\left[2f(Y_k, Y_{k-R_k}, \alpha_k)^\top g(Y_k, Y_{k-R_k}, \alpha_k)\Delta w_k\right] &= 0. \end{aligned} \quad (4.15)$$

Taking expectations on both sides of (4.14) and substituting (4.15) lead to

$$\begin{aligned} \mathbb{E}\left[\bar{p}_{k+1}|Z_{k+1}|^2\right] &= \mathbb{E}\left[\bar{p}_{k+1}|Z_k|^2\right] + \varepsilon^2\mathbb{E}\left[\bar{p}_{k+1}|f(Y_k, Y_{k-R_k}, \alpha_k)|^2\right] \\ &\quad + \varepsilon\mathbb{E}\left[\bar{p}_{k+1}\left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right)\right]. \end{aligned} \quad (4.16)$$

Step 3: We proceed to estimate the terms on the right hand side of (4.16). By the property of conditional expectation and (2.1), we have

$$\begin{aligned} \mathbb{E}\left[\bar{p}_{k+1}|Z_k|^2\mathbf{1}_{\{\alpha_{k+1}=\alpha_k\}}\right] &= \mathbb{E}\left[\mathbb{E}\left[\bar{p}_k|Z_k|^2\mathbf{1}_{\{\alpha_{k+1}=\alpha_k\}}\middle|\alpha_k\right]\right] \\ &= \mathbb{E}\left[\mathbb{E}\left[\bar{p}_k|Z_k|^2\middle|\alpha_k\right]\mathbb{E}\left[\mathbf{1}_{\{\alpha_{k+1}=\alpha_k\}}\middle|\alpha_k\right]\right] \\ &= \mathbb{E}\left[\mathbb{E}\left[\bar{p}_k|Z_k|^2\middle|\alpha_k\right]\sum_{i\in\mathcal{M}}\mathbf{1}_{\{\alpha_k=i\}}(1+q_{ii}\varepsilon+\varepsilon^2\tau_{ii}(\varepsilon))\right]. \end{aligned} \quad (4.17)$$

In the derivation above, we have utilized the fact that $\mathbf{1}_{\{\alpha_{k+1}=\alpha_k\}}$ and $\mathcal{F}_{k\varepsilon}$ are independent given α_k and the fact that $\mathbb{P}(\alpha_{k+1} = i|\alpha_k = i) = 1 + q_{ii}\varepsilon + \varepsilon^2\tau_{ii}(\varepsilon)$ for any $i \in \mathcal{M}$. Consequently, (4.17) impliest

$$\begin{aligned} \mathbb{E}\left[\bar{p}_{k+1}|Z_k|^2\mathbf{1}_{\{\alpha_{k+1}=\alpha_k\}}\right] &= \sum_{i\in\mathcal{M}}\mathbb{E}\left[\bar{p}_k|Z_k|^2\mathbf{1}_{\{\alpha_k=i\}}\right] + \sum_{i\in\mathcal{M}}\mathbb{E}\left[p_i|Z_k|^2\mathbf{1}_{\{\alpha_k=i\}}(q_{ii}\varepsilon+\varepsilon^2\tau_{ii}(\varepsilon))\right] \\ &= \mathbb{E}\left[\bar{p}_k|Z_k|^2\right] + \sum_{i\in\mathcal{M}}\mathbb{E}\left[p_i|Z_k|^2\mathbf{1}_{\{\alpha_k=i\}}(q_{ii}\varepsilon+\varepsilon^2\tau_{ii}(\varepsilon))\right]. \end{aligned} \quad (4.18)$$

Similarly,

$$\mathbb{E}\left[\bar{p}_{k+1}|Z_k|^2\mathbf{1}_{\{\alpha_{k+1}\neq\alpha_k\}}\right] = \sum_{i\in\mathcal{M}}\sum_{j\neq i}\mathbb{E}\left[p_j|Z_k|^2\mathbf{1}_{\{\alpha_k=i\}}(q_{ij}\varepsilon + \varepsilon^2\tau_{ij}(\varepsilon))\right]. \quad (4.19)$$

In view of (4.18) and (4.19),

$$\begin{aligned}\mathbb{E}\left[\bar{p}_{k+1}|Z_k|^2\right] &= \mathbb{E}\left[\bar{p}_k|Z_k|^2\right] + \sum_{i\in\mathcal{M}}\sum_{j\in\mathcal{M}}\mathbb{E}\left[r_j|Z_k|^2\mathbf{1}_{\{\alpha_k=i\}}(q_{ij}\varepsilon + \varepsilon^2\tau_{ij}(\varepsilon))\right] \\ &= \mathbb{E}\left[\bar{p}_k|Z_k|^2\right] + \sum_{j\in\mathcal{M}}\mathbb{E}\left[p_j|Z_k|^2(q_{\alpha_k j}\varepsilon + \varepsilon^2\tau_{\alpha_k j}(\varepsilon))\right];\end{aligned}$$

that is,

$$\mathbb{E}\left[\bar{p}_{k+1}|Z_k|^2\right] = \mathbb{E}\left[\bar{p}_k|Z_k|^2\right] + \sum_{j\in\mathcal{M}}\mathbb{E}\left[p_j|Z_k|^2(q_{\alpha_k j}\varepsilon + \varepsilon^2\tau_{\alpha_k j}(\varepsilon))\right]. \quad (4.20)$$

Similarly,

$$\begin{aligned}\mathbb{E}\left[\bar{p}_{k+1}\left(Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right)\right] \\ = \mathbb{E}\left[\bar{p}_k\left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right)\right] \\ + \sum_{j\in\mathcal{M}}\mathbb{E}\left[\bar{p}_j\left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right)(q_{\alpha_k j}\varepsilon + \varepsilon^2\tau_{\alpha_k j}(\varepsilon))\right].\end{aligned} \quad (4.21)$$

Substituting (4.20) and (4.21) into (4.16), we arrive at

$$\begin{aligned}\mathbb{E}\left[\bar{p}_{k+1}|Z_{k+1}|^2\right] &= \mathbb{E}\left[\bar{p}_k|Z_k|^2\right] \\ &+ \varepsilon\mathbb{E}\left[\bar{p}_k\left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right) + \sum_{j\in\mathcal{M}}(p_j|Z_k|^2q_{\alpha_k j})\right] \\ &+ \varepsilon^2\mathbb{E}\left[\bar{p}_{k+1}|f(Y_k, Y_{k-R_k}, \alpha_k)|^2\right] \\ &+ \varepsilon\sum_{j\in\mathcal{M}}\mathbb{E}\left[p_j\left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2\right)(q_{\alpha_k j}\varepsilon + \varepsilon^2\tau_{\alpha_k j}(\varepsilon))\right].\end{aligned} \quad (4.22)$$

Step 4: We proceed to estimate the terms on the right hand side of (4.22). Let

$$r_0 = \left(\sum_{j\in\mathcal{M}}p_j\right)\left(\exp(m_0\|Q\|_\infty) - (m_0 - 1)\|Q\|_\infty + 1\right);$$

see Remark 4.2. Noting that $\varepsilon \in (0, 1)$, we have $\varepsilon^2 < \varepsilon$. Furthermore, in view of (4.7), we have

$$\begin{aligned}|q_{\alpha_k j}\varepsilon + \varepsilon^2\tau_{\alpha_k j}(\varepsilon)| &\leq (\|Q\|_\infty + |\tau_{\alpha_k j}(\varepsilon)|)\varepsilon \\ &\leq \left(\exp(m_0\|Q\|_\infty) - 1 - (m_0 - 1)\|Q\|_\infty\right)\varepsilon.\end{aligned}$$

Hence,

$$\sum_{j \in \mathcal{M}} p_j |q_{\alpha_k j} \varepsilon + \varepsilon^2 \tau_{\alpha_k j}(\varepsilon)| \leq r_0 \varepsilon.$$

Using (4.8) together with the definition of r_0 , we obtain

$$\varepsilon^2 \mathbb{E} \left[\bar{p}_{k+1} |f(Y_k, Y_{k-R_k}, \alpha_k)|^2 \right] \leq \varepsilon^2 r_0 C_0 \mathbb{E} \left[|Y_k|^2 + |Y_{k-R_k}|^2 \right]. \quad (4.23)$$

We observe that

$$|Z_k|^2 \leq (1 + \kappa^2)(|Y_k|^2 + |Y_{k-1-R_{k-1}}|^2) \leq 2|Y_k|^2 + 2|Y_{k-1-R_{k-1}}|^2.$$

It follows from (3.1) that

$$\begin{aligned} & 2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2 \\ & \leq \|Q\|_\infty |Z_k|^2 + c_1 |Y_k|^2 + c_2 |Y_{k-1-R_{k-1}}|^2 \\ & \leq (2\|Q\|_\infty + c_1) |Y_k|^2 + (2\|Q\|_\infty + c_2) |Y_{k-1-R_{k-1}}|^2. \end{aligned}$$

Hence

$$\begin{aligned} & \varepsilon \sum_{j \in \mathcal{M}} \mathbb{E} \left[p_j \left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2 \right) (q_{\alpha_k j} \varepsilon + \varepsilon^2 \tau_{\alpha_k j}(\varepsilon)) \right] \\ & \leq \varepsilon^2 r_0 \left((2\|Q\|_\infty + c_1) \mathbb{E} |Y_k|^2 + (2\|Q\|_\infty + c_2) \mathbb{E} |Y_{k-1-R_{k-1}}|^2 \right). \end{aligned} \quad (4.24)$$

Utilizing (4.23) and (4.24) in (4.22), we deduce

$$\begin{aligned} & \mathbb{E} \left[\bar{p}_{k+1} |Z_{k+1}|^2 \right] \leq \mathbb{E} \left[\bar{p}_k |Z_k|^2 \right] \\ & + \varepsilon \mathbb{E} \left[\bar{p}_k \left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2 \right) + \sum_{j \in \mathcal{M}} (p_j |Z_k|^2 q_{\alpha_k j}) \right] \\ & + \varepsilon^2 r_0 \left((2\|Q\|_\infty + c_1 + C_0) \mathbb{E} |Y_k|^2 + C_0 \mathbb{E} |Y_{k-R_k}|^2 + (2\|Q\|_\infty + c_2) \mathbb{E} |Y_{k-1-R_{k-1}}|^2 \right). \end{aligned} \quad (4.25)$$

By (3.1),

$$\begin{aligned} & \bar{p}_k \left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2 \right) + \sum_{j \in \mathcal{M}} (p_j |Z_k|^2 q_{\alpha_k j}) \\ & \leq -c_0 \bar{p}_k |Z_k|^2 + c_1 \bar{p}_k |Y_k|^2 + c_2 \bar{p}_k |Y_{k-1-R_{k-1}}|^2. \end{aligned}$$

Hence,

$$\begin{aligned} & \varepsilon \mathbb{E} \left[\bar{p}_k \left(2Z_k^\top f(Y_k, Y_{k-R_k}, \alpha_k) + |g(Y_k, Y_{k-R_k}, \alpha_k)|^2 \right) + \sum_{j \in \mathcal{M}} (p_j |Z_k|^2 q_{\alpha_k j}) \right] \\ & \leq \varepsilon \left(-c_0 \mathbb{E} [\bar{p}_k |Z_k|^2] + c_1 \mathbb{E} [\bar{p}_k |Y_k|^2] + c_2 \mathbb{E} [\bar{p}_k |Y_{k-1-R_{k-1}}|^2] \right). \end{aligned} \quad (4.26)$$

Substituting (4.26) into (4.25) yields

$$\begin{aligned} \mathbb{E}[\bar{p}_{k+1}|Z_{k+1}|^2] &\leq (1 - \varepsilon c_0)\mathbb{E}[\bar{p}_k|Z_k|^2] + \varepsilon c_1\mathbb{E}[\bar{p}_k|Y_k|^2] + \varepsilon c_2\mathbb{E}[\bar{p}_k|Y_{k-1-R_{k-1}}|^2] \\ &\quad + \varepsilon^2 r_0 \left((2\|Q\|_\infty + c_1 + C_0)\mathbb{E}|Y_k|^2 + C_0\mathbb{E}|Y_{k-R_k}|^2 + (2\|Q\|_\infty + c_2)\mathbb{E}|Y_{k-1-R_{k-1}}|^2 \right). \end{aligned}$$

Applying Lemma 4.1, we find

$$\begin{aligned} \mathbb{E}[\bar{p}_{k+1}|Z_{k+1}|^2] &\leq (1 - \varepsilon c_0)K_1 e^{-\lambda k \varepsilon} + \varepsilon c_1 K_1 r_p \beta(\varepsilon) e^{-\lambda k \varepsilon} + \varepsilon c_2 K_1 r_p \beta(\varepsilon) e^{\lambda(r+\varepsilon)} e^{-\lambda k \varepsilon} \\ &\quad + \varepsilon^2 r_0 \beta(\varepsilon) K_1 p_{\min}^{-1} e^{-\lambda k \varepsilon} \left((2\|Q\|_\infty + c_1 + C_0) + C_0 e^{\lambda R_k \varepsilon} + (2\|Q\|_\infty + c_2) e^{\lambda(1+R_{k-1})\varepsilon} \right) \\ &\leq K_1 e^{-\lambda k \varepsilon} \left(1 + \varepsilon \left[-c_0 + c_1 r_p \beta(\varepsilon) + c_2 r_p e^{\lambda(r+\varepsilon)} + \varepsilon C_1(\varepsilon) \right] \right), \end{aligned}$$

where

$$C_1(\varepsilon) = \varepsilon r_0 \beta(\varepsilon) p_{\min}^{-1} \left((2\|Q\|_\infty + c_1 + C_0) + C_0 e^{\lambda r} + (2\|Q\|_\infty + c_2) e^{\lambda(1+r)\varepsilon} \right).$$

By (4.11), we have

$$\mathbb{E}[\bar{p}_{k+1}|Z_{k+1}|^2] \leq K_1 e^{-\lambda k \varepsilon} (1 - \varepsilon \lambda). \quad (4.27)$$

Since $\varepsilon < \varepsilon_0 < 1/\lambda_0$ and $\lambda < \lambda_0$, then $0 < 1 - \varepsilon \lambda < e^{-\lambda \varepsilon}$. It follows from (4.27) that

$$\mathbb{E}[\bar{p}_{k+1}|Z_{k+1}|^2] < K_1 e^{-\lambda(k+1)\varepsilon};$$

that is, $\Phi_{k+1} < \Psi_{k+1}$. This stands in contradiction to the second inequality in (4.13). As a result, (4.12) holds; that is,

$$\mathbb{E}[\bar{p}_n|Z_n|^2] \leq K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2 \quad \text{for } n \in \mathbb{N}_0.$$

By Lemma 4.1,

$$\mathbb{E}|Y_n|^2 \leq p_{\min}^{-1} \beta(\varepsilon) K e^{-\lambda n \varepsilon} \mathbb{E}\|\xi\|^2 \quad \text{for } n \in \mathbb{N}_0.$$

Thus, we conclude that the EM approximation (4.1) is mean-square exponentially stable, and the inequality (4.9) is satisfied. \square

Remark 4.4. Let the assumptions of Theorem 4.3 hold. Then the proof of Theorem 4.3 provides guidance for choosing the step size ε in the numerical experiments. Indeed, let a positive constant $\varepsilon_0 < (1/\lambda_0) \vee (-\frac{2}{\lambda} \ln \kappa - r)$ that satisfies condition (4.10). Then for any $\varepsilon \in (0, \varepsilon_0]$, the EM approximation $\{Y_n\}$ given by (4.1) is mean-square exponentially stable.

To illustrate the theoretical results derived in the previous sections, we present the following numerical example.

Example 4.5. Consider the scalar NSDDE given by

$$\begin{aligned} d(X(t) - G(X(t - \delta(t)), \alpha(t))) &= f(X(t), X(t - \delta(t)), \alpha(t))dt \\ &\quad + g(X(t), X(t - \delta(t)), \alpha(t))dw(t) \quad \text{for } t \geq 0, \end{aligned} \quad (4.28)$$

where the state space of the Markov chain $\alpha(t)$ is $\mathcal{M} = \{1, 2\}$ and the time-dependent delay is $\delta(t) = 2 - \cos t$ for $t \geq 0$. The coefficients of Eq. (4.28) are specified as

$$\begin{aligned} G(y, 1) &= 0.05y, \quad f(x, y, 1) = -1.1x + 0.2y, \quad g(x, y, 1) = 0.3x \cos y, \\ G(y, 2) &= 0.1y, \quad f(x, y, 2) = 0.2x + 0.1y, \quad g(x, y, 2) = 0.2 \sin y \end{aligned}$$

for $(x, y) \in \mathbb{R}^2$. Note that here the delay bound is $r = 3$ and the contraction constant is $\kappa = 0.1$.

It is instructive to examine the subsystems associated with Eq. (4.28). They correspond to the two states of the Markov chain:

$$\begin{aligned} d(X^{(1)}(t) - 0.05X^{(1)}(t - \delta(t))) &= (-1.1X^{(1)}(t) + 0.2X^{(1)}(t - \delta(t)))dt \\ &\quad + 0.3X^{(1)}(t) \cos(X^{(1)}(t - \delta(t)))dw(t), \end{aligned} \quad (4.29)$$

and

$$\begin{aligned} d(X^{(2)}(t) - 0.1X^{(2)}(t - \delta(t))) &= (0.2X^{(2)}(t) + 0.1X^{(2)}(t - \delta(t)))dt \\ &\quad + 0.2 \sin(X^{(2)}(t - \delta(t)))dw(t). \end{aligned} \quad (4.30)$$

The system switches between these two modes according to the evolution of $\alpha(t)$.

Note that Eq. (4.29) and Eq. (4.30) can be viewed as special cases of Eq. (2.2). Let $\{Y_n^{(1)}\}$ and $\{Y_n^{(2)}\}$ denote the EM approximation sequences for $X^{(1)}(t)$ and $X^{(2)}(t)$, respectively. For illustration purposes, we display the graphs of the sequences $\{\mathbb{E}|Y_n^{(1)}|^2\}$ and $\{\mathbb{E}|Y_n^{(2)}|^2\}$ in Figure 1 and Figure 2, using the initial condition $\xi(t) = 1 + \sin(1 - t)$. The expectation $\mathbb{E}|Y_n^{(i)}|^2$ is approximated by averaging over 100 simulation paths. What do these numerical results suggest? They indicate that Eq. (4.29) is likely mean-square exponentially stable, whereas Eq. (4.30) appears to be unstable.

Suppose the generator of $\alpha(t)$ is given by $Q = \begin{bmatrix} -1 & 1 \\ 3 & -3 \end{bmatrix}$. Our task now is to examine the mean-square exponential stability of the exact solutions and numerical approximations of the coupled system (2.2). It is worth noting that in this case, $\sup_{t \geq 0} \delta'(t) = 1$. Consequently, the existing stability criteria in the literature—particularly those in [3, 18, 28]—are not applicable.




Figure 1: Graph of $\{\mathbb{E}|Y_n^{(1)}|^2\}$ for the EM approximation $\{Y_n^{(1)}\}$ of Eq. (4.29). The expectation is estimated by averaging over 100 simulations.




Figure 2: Graph of $\{\mathbb{E}|Y_n^{(2)}|^2\}$ for the EM approximation $\{Y_n^{(2)}\}$ of Eq. (4.30). The expectation is estimated by averaging over 100 simulations.

We proceed by verifying assumption (H). Let us choose $p_1 = 0.5$ and $p_2 = 1$. We compute:

$$\begin{aligned}
& 2(x - G(y, 1))f(x, y, 1) + |g(x, y, 1)|^2 + \sum_{j \in \mathcal{M}} q_{1j} \frac{p_j}{p_1} |x - G(y, 1)|^2 \\
&= 2(x - 0.05y)(-1.1x + 0.2y) + |0.3x \cos y|^2 - (x - 0.05y)^2 + 2(x - 0.05y)^2 \\
&\leq 2(x - 0.05y)(-1.1x + 0.055y + 0.145y) + 0.09x^2 + (x - 0.05y)^2 \\
&= -1.2(x - 0.05y)^2 + 2 \cdot 0.145xy - 0.0145y^2 + 0.09x^2 \\
&\leq -1.2(x - 0.05y)^2 + 0.145x^2 + 0.145y^2 - 0.0145y^2 + 0.09x^2 \\
&= -1.2(x - 0.05y)^2 + 0.235x^2 + 0.1305y^2
\end{aligned} \tag{4.31}$$

and

$$\begin{aligned}
& 2(x - G(y, 2))f(x, y, 2) + |g(x, y, 2)|^2 + \sum_{j \in \mathcal{M}} q_{2j} \frac{p_j}{p_2} |x - G(y, 2)|^2 \\
&= 2(x - 0.1y)(0.2x + 0.1y) + |0.2 \sin y|^2 + 1.5(x - 0.1y)^2 - 3(x - 0.1y)^2 \\
&\leq 2(x - 0.1y)(0.2x - 0.02y + 0.12y) + 0.04y^2 - 1.5(x - 0.1y)^2 \\
&= 0.4(x - 0.1y)^2 + 0.24xy - 0.024y^2 + 0.04y^2 - 1.5(x - 0.1y)^2 \\
&\leq -1.1(x - 0.1y)^2 + 0.12x^2 + 0.12y^2 - 0.024y^2 + 0.04y^2 \\
&= -1.1(x - 0.1y)^2 + 0.12x^2 + 0.136y^2.
\end{aligned} \tag{4.32}$$

In view of (4.31) and (4.32), assumption (H) is satisfied with the parameters

$$p_1 = 0.5, \quad p_2 = 1, \quad c_0 = 1.1, \quad c_1 = 0.235, \quad c_2 = 0.136.$$

Hence, we calculate $r_p = \max\{\frac{p_2}{p_1}, \frac{p_1}{p_2}\} = 2$. Then

$$-c_0 + \frac{r_p}{(1 - \kappa)^2}(c_1 + c_2) = -1.1 + \frac{2(0.235 + 0.136)}{(1 - 0.1)^2} < 0;$$

that is, condition (3.5) is satisfied. By virtue of Theorem 3.2, we conclude that Eq. (4.28) is mean-square exponentially stable. Furthermore, Theorem 4.3 implies that for a sufficiently small step size ε , the EM approximations of Eq. (4.28) preserve this stability.

Utilizing the EM approximation method with step size $\varepsilon = 0.001$, initial condition $\xi(t) = 1 + \sin(1 - t)$ for $t \in [-3, 0]$, and $i_0 = 2$, we present the graph of the sequence $\{\mathbb{E}|Y_n^{\xi, i_0}|^2\}$ in Figure 3. (The expectation is approximated by averaging over 100 simulations). We verify that the chosen step size $\varepsilon = 0.001$ satisfies the selection guidelines outlined in Remark 4.4. To further illustrate the behavior, the corresponding graph for the sequence $\{\frac{1}{n\varepsilon} \ln(\mathbb{E}|Y_n^{\xi, i_0}|^2)\}$ is shown in Figure 4. These graphical representations are consistent with our theoretical analysis, demonstrating that $\mathbb{E}|Y_n^{\xi, i_0}|^2$ exponentially converges to zero as n increases.




Figure 3: Graph of $\{\mathbb{E}|Y_n^{\xi, i_0}|^2\}$ for the EM approximation $\{Y_n^{\xi, i_0}\}$ of Eq. (4.28). The expectation is estimated by averaging over 100 simulations.




Figure 4: Graph of $\{\frac{1}{n\varepsilon} \ln (\mathbb{E}|Y_n^{\xi, i_0}|^2)\}$ for the EM approximation $\{Y_n^{\xi, i_0}\}$ of Eq. (4.28). The expectation is estimated by averaging over 100 simulations.

This example serves to highlight the stabilization effect of the Markovian switching component. Although the subsystem (4.30) appears unstable in isolation, the introduction of Markovian switching results in a system (4.28) that is mean-square exponentially stable.

5 Concluding remarks

In this paper, we have investigated the mean-square exponential stability of NSDDEs with Markovian switching. The essence of our contribution lies in the development of a novel comparison principle via contradiction for NSDDEs with Markovian switching. By employing this approach, we have established stability criteria for both exact solutions and Euler–Maruyama approximations without imposing restrictive differentiability conditions on the time-varying delay. Consequently, our results cover a broader class of delay functions than those typically found in the existing literature, demonstrating that the numerical scheme can faithfully reproduce the stability and decay rate of the underlying system.

This work opens up several avenues for future research. For instance, our stability analysis could likely be extended to other numerical methods, such as the theta-approximations presented in [15]. Although this paper focused on NSDDEs with a single time-delay, the methodology developed herein appears applicable to more general settings. We believe it can be adapted to treat NSDDEs with multiple delays or even more general neutral stochastic functional differential equations. Furthermore, it would be interesting and challenging to apply our techniques to analyze the stability of truncated Euler–Maruyama approximations for NSDDEs and SDDEs, as developed in [1]. Addressing these problems effectively may require the development of new analytic tools, and we plan to explore these research directions in our future work.

References

- [1] Q. Guo, X. Mao, R. Yue, The truncated Euler–Maruyama method for stochastic differential delay equations. *Numer Algorithms*. 2018;78:599–624.
- [2] V. Kolmanovskii, A. Myshkis, *Introduction to the theory and applications of functional differential equations*. Vol. 463. Springer Science & Business Media; 2013.
- [3] G. Lan, C. Yuan, Exponential stability of the exact solutions and θ -EM approximations to neutral SDDEs with Markov switching. *J. Comput. Appl. Math.* 2015; 285: 230–242.
- [4] L. Liu, Q. Zhu, Mean square stability of two classes of theta method for neutral stochastic differential delay equations. *J. Comput. Appl. Math.* 2016; 305: 55–67.
- [5] W. Mao, B. Chen, F. Wu, X. Mao, On the existence and asymptotic stability of hybrid stochastic systems with neutral term and non-differentiable time delay. *Systems Control Lett.* 178 (2023), Paper No. 105586, 12 pp.
- [6] X. Mao, C. Yuan, *Stochastic Differential Equations with Markovian Switching*, Imperial College Press, London, 2006.

- [7] X. Mao, *Stochastic differential equations and applications*, Elsevier, Cambridge, 2007.
- [8] M. Milošević, Almost sure exponential stability of solutions to highly nonlinear neutral stochastic differential equations with time-dependent delay and the Euler-Maruyama approximation. *Math. Comput. Modelling.* 2013; 57(3-4): 887–899.
- [9] M. Milošević, Implicit numerical methods for highly nonlinear neutral stochastic differential equations with time-dependent delay. *Appl. Math. Comput.* 2014; 244: 741–760.
- [10] H. Mo, X. Zhao, F. Deng, Exponential mean-square stability of the θ -method for neutral stochastic delay differential equations with jumps. *Internat. J. Systems Sci.* 2017; 48(3): 462–470.
- [11] H. Mo, L. Liu, M. Xing, F. Deng, B. Zhang, Exponential stability of implicit numerical solution for nonlinear neutral stochastic differential equations with time-varying delay and Poisson jumps. *Math. Methods Appl. Sci.* 2021; 44(7): 5574–5592.
- [12] H. Mo, X. Zhao, F. Deng, Mean-square stability of the backward Euler-Maruyama method for neutral stochastic delay differential equations with jumps. *Math. Methods Appl. Sci.* 2017; 40(5): 1794–1803.
- [13] P.H.A. Ngoc, New results on exponential stability in mean square of neutral stochastic equations with delays. *Internat. J. Control.* 2022; 95(11): 3030–3036.
- [14] P.H.A. Ngoc, K. Tran, On stability of numerical solutions of neutral stochastic delay differential equations with time-dependent delay. *Mathematical Methods in the Applied Sciences*, 2023; 46(9): 11246–11261.
- [15] P.H.A. Ngoc, T.N.B. Le, K. Tran, Exponential stability in mean square of theta approximations for neutral stochastic delay differential equations with Poisson jumps. *International Journal of Systems Science*. 2025.
- [16] S.I. Niculescu, *Delay effects on stability: a robust control approach*. Vol. 269. Springer; 2003.
- [17] M. Obradović, M. Milošević, Almost sure exponential stability of the θ -Euler-Maruyama method for neutral stochastic differential equations with time-dependent delay when $\theta \in [0, 1/2]$. *Filomat.* 2017; 31(18): 5629–5645.
- [18] M. Obradović, Maja, M. Milošević, Stability of a class of neutral stochastic differential equations with unbounded delay and Markovian switching and the Euler-Maruyama method. *J. Comput. Appl. Math.* 309 (2017), 244–266.
- [19] A. Petrović, M. Milošević, The truncated Euler-Maruyama method for highly nonlinear neutral stochastic differential equations with time-dependent delay. *Filomat.* 2021;35(7):2457–2484.
- [20] K. Tran, G. Yin, Impulsive stochastic functional differential equations with Markovian switching: study of exponential stability from a numerical solution point of view. *IMA Journal of Control and Information.* 2025; 42: 172–185.
- [21] A. Wu, S. You, W. Mao, X. Mao, L. Hu, On exponential stability of hybrid neutral stochastic differential delay equations with different structures. *Nonlinear Anal. Hybrid Syst.* 39 (2021), Paper No. 100971, 17 pp.
- [22] F. Wu, X. Mao, Numerical solutions of neutral stochastic functional differential equations. *SIAM J. Numer. Anal.* 2008; 46(4): 1821–1841.
- [23] G. Yin, C. Zhu, *Hybrid Switching Diffusions: Properties and Applications*, Springer, New York, 2010.
- [24] S. Zhou, Exponential stability of numerical solution to neutral stochastic functional differential equation. *Appl. Math. Comput.* 2015; 266: 441–461.
- [25] Z. Zong, F. Wu, G. Yin, And Z. Jin, Almost sure and pth-moment stability and stabilization of regime-switching jump diffusion systems, *SIAM J. Control Optim.* 2014; 52(4): 2595–2622.
- [26] Z. Zong, F. Wu, C. Huang, Exponential mean square stability of the theta approximations for neutral stochastic differential delay equations. *J. Comput. Appl. Math.* 2015; 286: 172–185.
- [27] Z. Zong, F. Wu, Exponential stability of the exact and numerical solutions for neutral stochastic delay differential equations. *Appl. Math. Model.* 2016; 40(1): 19–30.

- [28] Y. Zhang, R. Li, X. Huo, Switching-dominated stability of numerical solutions for hybrid neutral stochastic differential delay equations. *Nonlinear Anal. Hybrid Syst.* 2019; 33: 76–92.
- [29] S. Zhou, Z. Fang, Numerical approximation of nonlinear neutral stochastic functional differential equations. *J. Appl. Math. Comput.* 2013; 41(1-2): 427–445.